

## Reset the Down Stop position for ODS L10 MECH

This Down Limit position is preset by the manufacturer and is only required if the motor is being changed, or repairs are being carried on a damaged curtain.

- Put the curtain in the down position by pressing the down button on the E-Port 18650.
- Remove axle from the endplates: if it has a red axle insert, push in the 2 wings on the axle insert, this will then allow the axle insert to slide into the axle and shorten the axle.
- Push the down button on the E-Port 18650 control and the motor will cycle down, then stop.
- Push the down button again to lock its memory.
- Reconnect the axle to the endplates and close the boxing.

