

Telis 6 Chronis RTS

Deleting an automatic order




1 Enter programming mode



Toggle to automatic mode by briefly pressing the selection button.



Hold




Press and hold the selection button until SET appears on the display.


2 Select day to delete order



Use the navigation buttons to select the day to be modified.



Briefly press the selection button. EDIT and SET will appear on the display.



Use the navigation button until DELET appears on the display.




Briefly press the selection button.

Telis 6 Chronis RTS

Deleting an automatic order



3 Delete automatic order




Use the navigation button to select the automatic order to be deleted.



Briefly press the selection button. The automatic order is deleted.

4 Save changes



Press and hold the selection button to save changes.

Telis 6 Chronis RTS

Deleting an automatic order

